
CENTURION

REMOTE ORDERING OPTIONS

Art ID:
SGT180



SPECIFICATIONS
Centurion
Frequency -433Mhz
Buttons - 4
Battery - LR27A

COMPATIBLE WITH



TX4-R



TX4-B

RECEIVER COMPATIBILITY

- Suits Models:

Slimfit, N3588, SDO10, SDO-21 TP/BP, RDO10, T12/S12, MPS 12, MPS12, MPS 21, DPS D12/D20, SDO-3 DC, SDO-P, SDO-1, SDO-21 DPS, SDO-21 MPS

Remote Programming Steps

Program Remote to Receiver

1. Press the Learn/Code Set button once. (A light on the motor will start to flash slowly.)
2. Press the button on the new remote that you wish to operate the door once. (The light on the motor will extinguish.)
3. Press the same button on the new remote again once. (The light on the motor will flash rapidly.)
4. Once the light stops flashing, test new

Deleting All Remotes from Receiver

1. Press the LEARN or CODE SET button. (LED indicator will glow solid)
2. Press and hold the black RUN button (LED indicator will begin to flash quickly)
3. Once LED stops flahing all remotes are deleted

Whilst every effort has been made to ensure the accuracy of the information supplied herein, we assume no liability for any errors or omissions. Information contained in this document is subject to change without prior notice.